



MODEL 6508 ILLUMINATED ELECTRONIC CONTROL HEAD

The 6508 is an illuminated version of the many Kobelt control heads. It is made entirely in bronze and stainless steel but is not considered to be a water tight unit.

The 6508 control head can be equipped with two potentiometers per handle. This will give redundancy in the electronic control system. The microprocessor will read the two potentiometers at all times and if it considers one of them defective, it will read the one that is intact only. The

membrane key pad has four standard switches and provides:


Station Select
Station Lock
Overriding Throttle
Engine Synchronization

Trolling valve options are also available in place of either one of the above four switches. The membrane has back lit lenses that indicate which function is working.

Options:

Black Epoxy or Chrome Plated body. Handles are always chrome plated.

MODEL 6508 DIMENSIONS




All dimensions in inches (mm)

Weight: 9.9 lb. (4.5 kg)



DIMENSIONS AND PARTS LIST MODEL 6508



| Item | Qty | Part Number | Description | Item | Qty | Part Number | Description |
|------|-----|----------------|------------------|------|-----|----------------|------------------------|
| | | | • | | | | |
| 1 | 1 | 6508-0001 | Housing | 17 | 1 | 6654-0001 | Dome |
| 2 | 2 | 6508-0002 | Bracket | 18 | 1 | 6654-0002 | Frame |
| 3 | 2 | 6508-0003 | Cam | 19 | 2 | 6654-0016 | Scale Retainer |
| 4 | 2 | 6508-0004 | Spur Gear | 20 | 4 | 6654-0027 | Spacer |
| 5 | 2 | 6508-0005 | Pinion | 21 | 2 | 1005-0808 | Oval Hd Slotted Screw |
| 6 | 1 | 6012-0001 | Switch Pad | 22 | 2 | 1006-0603 | Pan Hd Slotted Screw |
| 7 | 2 | 6508-0007 | Handle | 23 | 10 | 1010-0804 | Round Hd Philips Screw |
| 8 | 2 | 6001-0249 | Connection Gland | 24 | 16 | 1011-0406 | Oval Hd Philips Screw |
| 9 | 1 | 6509-0002 | Spacer | 25 | 12 | 1012-0606 | Pan Hd Philips Screw |
| 10 | 1 | 6509-0003 | Cover | 26 | 4 | 1016-1104 | Hex Socket Set Screw |
| 11 | 1 | 6509-0009 | Circuit Board | 27 | 4 | 1016-1004 | Hex Socket Set Screw |
| 12 | 1 | 6522-0006 | Scale | 28 | 2* | 1016-0804 | Hex Socket Set Screw |
| 13 | 1 | 6522-0007 | Scale | 29 | 2 | 1201-0002 | Spring |
| 14 | 2 | 2553-0018 | Pointer | 30 | 2 | 1201-0003 | Spring |
| 15 | 1 | 6541-0001 | Circuit Board | 31 | 4 | 1001-0810 | Hex Hd Cap Screw |
| 16 | 2 | POT-5 | Potentiometer 5K | 32 | 2 | 2542-0008 | Friction Pad |
| | | | | 33 | 2 | 2009-0011 | Detent Plug |

^{*} items not shown

